IN THE CLAIMS

1.   (Currently Amended) An I/Q demodulator comprising:

an n-port structure being supplied with a first RF signal to be demodulated at a

first input and with a second RF signal to be demodulated at a second input, said n-port structure

outputting n-2 output signals of a plurality of power sensors, with n being 4, 5 or 6, and

a multiplexing means for multiplexing low-pass-filtered output signals of the

plurality of power sensors to a single output.

2.   (Previously Presented) The I/Q demodulator according to claim 1,

wherein said I/Q demodulator further comprises a single A/D converter that is supplied with an

analog signal originating from the multiplexing means and outputting a digitally converted signal

to a digital processing unit.

3.   (Previously Presented) The I/Q demodulator according to claim 2,

wherein the A/D converter has an adaptive sampling rate.

4.   (Previously Presented) The I/Q demodulator according to claim 2,

wherein the digital processing unit comprises an adaptive baseband filtering unit.

5.   (Previously Presented) The I/Q demodulator according to claim 1,

wherein the output signals of the plurality of power sensors are selectively passed through

different low-pass-filters having different cut-off-frequencies.

6.   (Previously Presented) The I/Q demodulator according to claim 5, wherein said I/Q demodulator further comprises switches for selecting the different low-pass-filters.

7.   (Previously Presented) The I/Q demodulator according to claim 1, wherein the n-port structure is a five-port-junction.

8.   (Previously Presented) The I/Q demodulator according to claim 1, wherein the n-port structure is a four-port-junction and the demodulator is a (M)QAM or a (M)PSK demodulator.

9.   (Previously Presented) The /Q demodulator according to claim 1, wherein the multiplexing means is a DC-switch with a switching time of $\dfrac{1}{n-2}$ times a symbol duration.

10.   (Previously Presented) The 1/Q demodulator according to claim 1, wherein before or after the multiplexing means at least one DC-amplifier is provided.

11.   (Previously Presented) The I/Q demodulator according to claim 1, further comprising a low-pass-filter following the multiplexing means and, said low-pass filter having a cut-off-frequency of $\dfrac{n-2}{2} B$, whereby the output signals of the plurality of power sensors are low-pass-filtered with a cut-off-frequency of $\dfrac{B}{2}$, where B is a maximum bandwidth of the RF signal to be demodulated.

12.   (Previously Presented) The I/Q demodulator according to claim 1,

wherein the n-port structure, the plurality of power sensors and said multiplexing means are

integrated on a single chip.

13.   (Previously Presented) A software radio device wherein said radio device

comprises an I/Q-demodulator according to claim 1.

14.   (Currently Amended) A method for I/Q-demodulation, said method

comprising the steps of:

inputting a first RF signal to be demodulated in an n-port structure,

inputting a second RF signal in an n-port structure,

detecting the power of n-2 output signals of a plurality of output sensors of the n-

port structure, n being 4, 5 or 6,

low-pass-filtering the detected power signals, and

multiplexing the low-pass-filtered power signals to a single output.

15.   (Previously Presented) The method according to claim 14, said method

further comprising the step of:

supplying a single A/D converter with the multiplexed power signals and

outputting a digitally converted signal to a digital processing unit.

16.   (Previously Presented) The method according to claim 15, said method

further comprising the step of:

adapting a sampling rate of the A/D converter depending on a bandwidth of the

RF signal to be demodulated.

17.   (Previously Presented) The method according to claim 14, wherein the

power signals are selectively filtered with different cut-off-frequencies.

18.   (Previously Presented) The method according to claim 14, wherein the

step of multiplexing is implemented by a DC-switch with a switching time $\dfrac{1}{n-2}$ of a symbol

duration.

19.   (Previously Presented) The method according to claim 14, wherein the

multiplexed power signals are low-pass-filtered with a cut-off-frequency of $\dfrac{n-2}{2}B$, whereby

non-multiplexed power signals are low-pass-filtered with the a cut-off-frequency of $\dfrac{B}{2}$ } , where

B is a maximum bandwidth of the RF signal to be demodulated.